


KP 12 CLD GPIO Option Expansion Unit Installation Instructions

IMPORTANT: Once you have finished installing the GPIO Expansion Unit, you must perform a Reset Cfg on the unit.

To install the KP 12 CLD GPIO Expansion Panel, do the following:

1. On the rear of the KP 12 CLD, remove the **two (2) hex screws** on either side of the DB-9 connector.



2. Align the **mounting tab** located on the front of the KP 12 CLD GPIO expansion unit with the **mounting tab slot** located on the rear of the KP 12 CLD unit. See Figure 1.

IMPORTANT: Do not attach the GPIO expansion unit mounting tab to the KP 12 CLD unit. Attaching the unit with this one (1) screw may cause the chassis to bend or be damaged. Continue to step 2.




FIGURE 1. GPIO Expansion Unit — Mounting Tab Alignment with KP 12 CLD

RTS Digital Matrix Intercom

Innovating the Future of Communications

- Using the screws provided, attach the **GPIO Expansion Unit** to the rear panel of the KP 12 CLD unit (see Figure 2).




FIGURE 2. GPIO Expansion Unit — Attachment Points

- Using the screw provided, attach the **mounting tab to the mounting tab slot**. See Figure 3.




FIGURE 3. Mounting Tab Screw Hole