

Telex Communications Inc.

Pro Sound & Entertainment Group

How To Guide #

Update Adam AIO Card Firmware Via ADAMEDIT

Author:- Struan Robertson

Date:- 05 May 1998

Issue:- 1.0

1. Table Of Contents

1. Table Of Contents	2
2. Issue Status	2
3. Requirements.....	2
4. Procedure.....	2

2. Issue Status

Issue	Date	Reason
1.0	05 May 1998	

3. Requirements

- Computer running ADAMEDIT
- The new Hex file for the AIO card

4. Procedure

The following has to be carried out to update the AIO firmware in the Adam Matrix.

Please follow the following procedure:-

1. Place the **Hex** file into a temp directory
2. Open ADAM EDIT and ensure that you are online.
3. Select Status from the pop downs along the top of the screen.
4. Select Software Versions.
5. Select IO Card.
6. It should show the current version on all the cards fitted
7. Highlight them using the Shift and arrow keys. Note that due to the memory that this uses on the Controller cards it is best to only select 5 AIO cards at one time.
8. Now do the following keystroke **Ctrl + Shift ^ and D**.
9. A dialogue box named **Firmware Download** should appear.
10. From the Temp directory created earlier select the **Hex** file, select OK
11. You now should have a dialogue box named **Download Device Firmware**.
12. Select **Begin Download**.
13. The download bar should show the % . This takes a few minutes.
14. When this is complete the AIO's will reset.
15. Wait a minute.
16. Confirm that the AIO cards now have the new version .